

F

eatures:

- 4 outlet for Nema Type
- Desktop and Wall Mount Design
- User-friendly Visual Indicators Display
- Automatically Regulating High Voltage and Low Voltage
- Able to reset Input Overload Protection Circuit Breaker

Applications: Personal Computers and Small Electronic Devices

S

pecification:

Model		AVR-800
Capacity		800VA/360W
AC Input	Nominal Voltage	120VAC
	Input Voltage Range	96VAC ~ 140VAC
	Phase	1 Phase 2 Wires
	Frequency	50/60Hz (auto sensing)
AC Output	Output Voltage Range	107VAC ~ 132VAC
	Frequency	50 or 60Hz
Outlets	Surge Plus AVR Protection	4 Nema 5-15R
Protection	Network Surge Suppression	none
	Overload	Manual Reset Circuit Switch
	Short Circuit	Manual Reset Circuit Switch
LED	Regulation	Green LED
Environment	Operating Environment	0 ~ 40°C
	Relative Humidity	0 ~ 95%, non-condensing
	Audible Noise	< 40 dB at 1meter
Physical	Dimension(W*H*D) in./mm	
	Net Weight	2.65lbs / 1.2kg
Warranty		3 years limited

*Specifications may change at any time without notice.
 *All trade marks belong to their respected owners.